ONFI Technical Errata

Errata ID	**001**
Affected Spec Ver.	**ONFI 2.0**
Corrected Spec Ver.	

Submission info

Name	Company	Date
Amber Huffman	Intel	2/7/2008

Description of the specification technical flaw (add space as needed)

There is a common implementation of the Copyback2 command in the industry that uses opcodes 3Ah and 8Ch. This erratum places these opcodes in the Future Standardization category such that the Copyback2 command may be standardized in the future.

Description of the correction

Modify Table 37 as shown:

Type	Opcode
Vendor Specific	02h – 04h, 08h, 16h – 17h, 19h, 1Dh, 20h – 22h, 25h – 29h, 2Bh, 2Dh – 2Fh, 33h, 36h – 39h, 3Bh – 3Eh, 40h – 41h, 48h, 4Ch, 53h – 55h, 68h, 72h – 75h, 84h, 87h – 89h, 91h – BFh, CFh, F1-F4h
Future Standardization	06h, 23h – 24h, 2Ah, 2Ch, 32h, 34h, 3Ah, 65h, 71h, 79h – 7Bh, 81h, 8Ch
Block Abstracted NAND	C0h - CEh
Reserved	01h, 07h, 09h – 0Fh, 12h-14h, 18h, 1Ah – 1Ch, 1Eh – 1Fh, 42h – 47h, 49h – 4Bh, 4Dh – 52h, 56h – 5Fh, 61h – 64h, 66h – 67h, 69h – 6Fh, 76h – 77h, 7Ch – 7Fh, 82h – 83h, 86h, 8Ah – 8Bh, 8Dh – 8Fh, D2h –DFh, E1h – EBh, F0h, F5h – FBh, FDh – FEh

Table 1 Opcode Reservations

Disposition log

2/7/2008	Erratum captured.
3/24/2008	Erratum ratified.

Technical input submitted to the ONFI Workgroup is subject to the terms of the ONFI contributor's agreement.